

Rockwell Automation Support Center

165251 - ControlLogix Redundancy Firmware Bundle Revision History

Access Level: TechConnect

Date Created: 04/21/2011 08:45 AM

Last Updated: 03/12/2013 03:26 PM

Question

What ControlLogix Redundancy Bundles have been available for download and what revisions did they contain?

Answer

ControlLogix Enhanced Redundancy Systems

20.054 Enhanced_kit1	
Release Notes attached below: 1756-RN694D-EN-P	
Available for download from the Firmware Updates web site.	
<ul style="list-style-type: none"> Added support for 1756-RM2 	
Catalog Number	Revision
1756-L61	20.054.110
1756-L62	20.054.110
1756-L63, 1756-L63XT	20.054.110
1756-L64	20.054.110
1756-L65	20.054.110
1756-L71	20.054.110
1756-L72	20.054.110
1756-L73, 1756-L73XT	20.054.110
1756-L74	20.054.110
1756-L75	20.054.110
1756-CN2	20.020.602800
1756-CN2R, 1756-CN2RXT	20.020.602800
1756-EN2T, 1756-EN2TXT	5.008.700300
1756-EN2TR	5.008.700300
1756-EN2F	5.008.700300
1756-RM, 1756-RMXT	3.003.7
1756-RM2, 1756-RM2XT	20.004

20.054 Enhanced	
Release Notes attached below: 1756-RN694A, 1756-RN694B	
Catalog Number	Revision
1756-L61	20.054.110
1756-L62	20.054.110
1756-L63, 1756-L63XT	20.054.110
1756-L64	20.054.110
1756-L65	20.054.110
1756-L71	20.054.110
1756-L72	20.054.110
1756-L73, 1756-L73XT	20.054.110
1756-L74	20.054.110
1756-L75	20.054.110
1756-CN2	20.020.602800
1756-CN2R, 1756-CN2RXT	20.020.602800
1756-EN2T, 1756-EN2TXT	5.008.700300
1756-EN2TR	5.008.700300
1756-EN2F	5.008.700300

1756-RM, 1756-RMXT	3.003.7
--------------------	---------

19.053 Enhanced_kit1

Release Notes attached below: 1756-RN684D

Available for download from the [Firmware Updates](#) web site.

- Added support for 1756-RM2

Catalog Number	Revision
1756-L61	19.52.239
1756-L62	19.52.239
1756-L63, 1756-L63XT	19.52.239
1756-L64	19.52.239
1756-L65	19.52.239
1756-L72	19.53.251
1756-L73, 1756-L73XT	19.53.251
1756-L74	19.53.251
1756-L75	19.53.251
1756-CN2	20.13.501400
1756-CN2R, 1756-CN2RXT	20.13.501400
1756-EN2T, 1756-EN2TXT	4.3.501500
1756-EN2TR	4.004
1756-RM, 1756-RMXT	3.2.36
1756_RM2, 1756-RM2XT	20.004

19.053 Enhanced (October 2011)

Release Notes attached below: 1756-RN684C

- Changed 1756-EN2TR FW rev to 4.004
- Added more XT modules in the list

Catalog Number	Revision
1756-L61	19.52.239
1756-L62	19.52.239
1756-L63, 1756-L63XT	19.52.239
1756-L64	19.52.239
1756-L65	19.52.239
1756-L72	19.53.251
1756-L73, 1756-L73XT	19.53.251
1756-L74	19.53.251
1756-L75	19.53.251
1756-CN2	20.13.501400
1756-CN2R, 1756-CN2RXT	20.13.501400
1756-EN2T, 1756-EN2TXT	4.3.501500
1756-EN2TR	4.004
1756-RM, 1756-RMXT	3.2.36

19.053 Enhanced

Release Notes attached below: 1756-RN684B

- Added 19.53 firmware for 1756-L7x controllers

Catalog Number	Revision
1756-L61	19.52.239
1756-L62	19.52.239
1756-L63, 1756-L63XT	19.52.239
1756-L64	19.52.239
1756-L65	19.52.239

1756-L72	19.53.251
1756-L73	19.53.251
1756-L74	19.53.251
1756-L75	19.53.251
1756-CN2/B	20.13.501400
1756-CN2R/B	20.13.501400
1756-EN2T	4.3.501500
1756-EN2TR	4.3.501500
1756-RM, 1756-RMXT	3.2.36

19.052 Enhanced

Release Notes attached below: 1756-RN684A

Removed from web due to L7x firmware anomaly.

- Product Safety Advisory - 2011-04-005 - Answer ID 186811

Catalog Number	Revision
1756-L61	19.52.239
1756-L62	19.52.239
1756-L63, 1756-L63XT	19.52.239
1756-L64	19.52.239
1756-L65	19.52.239
1756-L72	19.52.241
1756-L73	19.52.241
1756-L74	19.52.241
1756-L75	19.52.241
1756-CN2/B	20.13.501400
1756-CN2R/B, 1756-CN2RXT/B	20.13.501400
1756-EN2T, 1756-EN2TXT	4.2.501400
1756-EN2T R	4.2.501400
1756-RM, 1756-RMXT	3.2.36

16.081 Enhanced_kit1

Release Notes attached below: 1756-RN650E-EN-E

Available for download from the [Firmware Updates](#) web site.

- Added support for 1756-RM2

Catalog Number	Revision
1756-L61	16.81.49
1756-L62	16.81.49
1756-L63, 1756-L63XT	16.81.49
1756-L64	16.81.49
1756-CN2	20.11.206600
1756-CN2R, 1756-CN2RXT	20.11.206600
1756-EN2T, 1756-EN2TXT	2.7.206600
1756-RM, 1756-RMXT	2.5.86
1756-RM2, 1756-RM2XT	20.004

16.081 Enhanced

Release Notes attached below: 1756-RN650D

<ul style="list-style-type: none"> • Corrected anomalies with ALMD and fault handlers • False execution time of AOI have been improved 	
Catalog Number	Revision
1756-L61	16.81.49
1756-L62	16.81.49
1756-L63	16.81.49
1756-L64	16.81.49
1756-CN2/B	20.11.206600
1756-CN2R/B, 1756-CN2RXT/B	20.11.206600
1756-EN2T, 1756-EN2TXT	2.7.206600
1756-RM/A, 1756-RMXT/A	2.5.86

16.080 Enhanced	
Release Notes attached below: 1756-RN650C	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Product Notice 2010-01-001 in Answer ID 66543 	
Catalog Number	Revision
1756-L61	16.80.47
1756-L62	16.80.47
1756-L63	16.80.47
1756-L64	16.80.47
1756-CN2/B	20.11.206600
1756-CN2R/B, 1756-CN2RXT/B	20.11.206600
1756-EN2T, 1756-EN2TXT	2.7.206600
1756-RM/A, 1756-RMXT/A	2.5.86

16.054 Enhanced	
Release Notes attached below: 1756-RN650B	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Product Notice 2010-01-001 in Answer ID 66543 • Product Notice 2008-11-003 in Answer ID 56914 	
Catalog Number	Revision
1756-L61	16.54.43
1756-L62	16.54.43
1756-L63	16.54.43
1756-L64	16.54.43
1756-CN2/B	20.009.204902
1756-CN2R/B	20.009.204902

1756-EN2T	2.003.205002
1756-RM/A	2.3.15

ControlLogix Standard Redundancy Systems

16.57 Standard_kit1	
Release Notes attached below: 1756-RN628M-EN-E	
Available for download from the Firmware Updates web site.	
<ul style="list-style-type: none"> Added support for 1756-RM2 	
Catalog Number	Revision
1756-L61	16.057.49
1756-L62	16.057.49
1756-L63	16.057.49
1756-L64	16.057.49
1756-CNBR/D	7.016.9
1756-CNBR/D	7.016.9
1756-CNBR/E	11.005.12
1756-CNBR/E	11.005.12
1756-ENBT	6.006.4
1756-EWEB	4.016
1756-RM	2.006.87
1756-RM2, 1756-RM2XT	20.004
1757-SRM	5.004.1

16.57 Standard_Aug2012	
Release Notes attached below: 1756-RN628L	
<ul style="list-style-type: none"> Anomalies fixed for 1756-ENBT and 1756-EWEB E0300 errors, 1757-SRM CRC errors Changed 1756-ENBT from 4.8 to 6.6 and 1757-SRM from revision 5.3 to 5.4 	
Catalog Number	Revision
1756-L61	16.057.49
1756-L62	16.057.49
1756-L63	16.057.49
1756-L64	16.057.49
1756-CNBR/D	7.016.9
1756-CNBR/D	7.016.9
1756-CNBR/E	11.005.12
1756-CNBR/E	11.005.12
1756-ENBT	6.006.4
1756-EWEB	4.016.4
1756-RM	2.006.87
1757-SRM	5.004.1

16.57 Standard	
Release Notes attached below: 1756-RN628K	
<ul style="list-style-type: none"> Corrected anomalies with fault handlers 	
Catalog Number	Revision
1756-L61	16.57.49
1756-L62	16.57.49

1756-L63	16.57.49
1756-L64	16.57.49
1756-CNB/D	7.16.9
1756-CNBR/D	7.16.9
1756-CNB/E	11.5.12
1756-CNBR/E	11.5.12
1756-ENBT	4.008
1756-EWEB	4.9.12
1756-RM/A	2.6.87
1757-SRM/A	5.003

16.56 Standard

Release Notes attached below: 1756-RN628J

Available upon special request, after reviewing:

- Product Notice 2010-01-001 in Answer ID [66543](#)

Catalog Number	Revision
1756-L61	16.56.47
1756-L62	16.56.47
1756-L63	16.56.47
1756-L64	16.56.47
1756-CNB/D	7.16.9
1756-CNBR/D	7.16.9
1756-CNB/E	11.5.12
1756-CNBR/E	11.5.12
1756-ENBT	4.8.14
1756-EWEB	4.9.12
1756-RM/A	2.6.87
1757-SRM/A	5.3.41

16.53 Standard

Release Notes attached below: 1756-RN628G

Available upon special request, after reviewing:

- Product Notice 2010-01-001 in Answer ID [66543](#)
- Product Notice 2008-11-003 in Answer ID [56914](#)

Catalog Number	Revision
1756-L61	16.53.42
1756-L62	16.53.42
1756-L63	16.53.42
1756-L64	16.53.42
1756-CNB/D	7.15.11
1756-CNBR/D	7.15.11
1756-CNB/E	11.4.14
1756-CNBR/E	11.4.14
1756-ENBT	4.7.19
1756-EWEB	4.8.14
1757-SRM	5.1.42

16.50 Standard

Release Notes attached below: 1756-RN628F	
Available upon request, after reviewing:	
<ul style="list-style-type: none"> Product Notice 2010-01-001 in Answer ID 66543 	
Catalog Number	Revision
1756-L61	16.52.41
1756-L62	16.52.41
1756-L63	16.52.41
1756-L64	16.52.41
1756-CNBR/D	7.15.11
1756-CNBR/D	7.15.11
1756-CNBR/E	11.4.14
1756-CNBR/E	11.4.14
1756-ENBT	4.7.19
1756-EWEB	4.8.14
1757-SRM	5.1.42

15.61 Standard	
Release Notes attached below: 1756-RN668A	
Available for download from the Firmware Updates web site.	
Catalog Number	Revision
1756-L55Mxx	15.61.1
1756-L61	15.61.1
1756-L62	15.61.1
1756-L63	15.61.1
1756-CNBR/D	7.13.4
1756-CNBR/D	7.13.4
1756-CNBR/E	11.3.7
1756-CNBR/E	11.3.7
1756-ENBT	4.4.24
1756-EWEB	4.4.24
1757-SRM	4.6.1

15.60 Standard	
Release Notes attached below: 1756-RN628E	
Available upon request, after reviewing:	
<ul style="list-style-type: none"> Product Notice 2009-08-002 in Answer ID 63365 Product Notice 2008-11-003 in Answer ID 56914 	
Catalog Number	Revision
1756-L55Mxx	15.60.50
1756-L61	15.60.50
1756-L62	15.60.50
1756-L63	15.60.50
1756-CNBR/D	7.13.4
1756-CNBR/D	7.13.4

1756-CNBE	11.3.7
1756-CNBR/E	11.3.7
1756-ENBT	4.4.24
1756-EWEB	4.4.24
1757-SRM	4.4.40

15.57/15.56 Standard

Release Notes attached below: 1756-RN628D

Available for download from the [Firmware Updates](#) web site.

- New CNB(R) ser E firmware 11.02
- New L55 firmware 15.57

Must review:

- Product Notice 2008-11-003 in Answer ID [56914](#)

Catalog Number	Revision
1756-L55Mxx	15.57.3
1756-L61	15.56.5
1756-L62	15.56.5
1756-L63	15.56.5
1756-CNBD	7.12.4
1756-CNBR/D	7.12.4
1756-CNBE	11.2.3
1756-CNBR/E	11.2.3
1756-ENBT	4.3.2
1756-EWEB	4.3.2
1757-SRM	4.3.5

15.56 Standard

Release Notes attached below: 1756-RN628C

Available internally for Techsupport only

- Anomalies with Controlnet modules fixed in the 15.56/57 revision

Catalog Number	Revision
1756-L55Mxx	15.56.5
1756-L61	15.56.5
1756-L62	15.56.5
1756-L63	15.56.5
1756-CNBD	7.12.4
1756-CNBR/D	7.12.4
1756-CNBE	11.1
1756-CNBR/E	11.1
1756-ENBT	4.3.2
1756-EWEB	4.3.2
1757-SRM	4.3.5

13.71 Standard

Release Notes attached below: 1756-RN608F

Available for download from the [Firmware Updates](#) web site.

Must review:

- Product Notice 2009-08-002 in Answer ID [63365](#)
- Product Notice 2008-11-003 in Answer ID [56914](#)

Catalog Number	Revision
1756-L55Mxx	13.70.70
1756-L61	13.71.20
1756-L62	13.71.20
1756-L63	13.71.20
1756-CNBR/D	5.51.10
1756-CNBR/D	5.51.10
1756-ENBT	3.7.3
1756-EWEB	2.4.2
1757-SRM	3.39.16

13.70 Standard

Release Notes attached below: 1756-RN608E

Available upon special request, after reviewing:

- Product Notice 2009-08-002 in Answer ID [63365](#)
- Product Notice 2008-11-003 in Answer ID [56914](#)

NOT for use in 1756-L6x/B revision 1.10 or higher controllers.

Catalog Number	Revision
1756-L55Mxx	13.70.70
1756-L61	13.70.70
1756-L62	13.70.70
1756-L63	13.70.70
1756-CNBR/D	5.46.40
1756-CNBR/D	5.46.40
1756-ENBT	3.7.3
1756-EWEB	2.4.2
1757-SRM	3.39.16

13.60 Standard

Release Notes attached below: 1756-RN608D

Available upon special request, after reviewing:

- Product Notice 2009-08-002 in Answer ID [63365](#)
- Product Notice 2008-11-003 in Answer ID [56914](#)

NOT for use in 1756-L6x/B revision 1.10 or higher controllers.

Catalog Number	Revision
1756-L55Mxx	13.53.30
1756-L61	13.53.30
1756-L62	13.53.30
1756-L63	13.53.30
1756-CNBR/D	5.45.10
1756-CNBR/D	5.45.10
1756-ENBT	3.4.2
1756-EWEB	2.2.8
1757-SRM	3.37.5

13.53 Standard

Release Notes attached below: 1756-RN608C	
Available for download from the Firmware Updates web site for SIL-2 systems.	
Must review:	
<ul style="list-style-type: none"> Product Notice 2009-08-002 in Answer ID 63365 Product Notice 2008-11-003 in Answer ID 56914 Service Advisory 2004-11-002 in Answer ID 53307 	
NOT for use in 1756-L6x/B revision 1.10 or higher controllers	
Catalog Number	Revision
1756-L55Mxx	13.53.30
1756-L61	13.53.30
1756-L62	13.53.30
1756-L63	13.53.30
1756-CNB/D	5.44.30
1756-CNBR/D	5.44.30
1756-ENBT	3.3.7
1756-EWEB	2.2.8
1757-SRM	3.37.5

11.72 Standard	
Release Notes attached below: 1756-RN582Q	
Available for download from the Firmware Updates web site after reviewing:	
Available upon special request, after reviewing:	
<ul style="list-style-type: none"> Service Advisory 2004-11-002 in Answer ID 53307 	
Catalog Number	Revision
1756-L55Mxx	11.72
1756-CNB/D	5.38.40
1756-CNBR/D	5.38.40
1756-ENBT	2.3
1757-SRM	3.29

11.71 Standard	
Release Notes attached below: 1756-RN582P	
Available upon special request, after reviewing:	
<ul style="list-style-type: none"> Service Advisory 2004-08-003 in Answer ID 53320 Service Advisory 2004-11-002 in Answer ID 53307 	
Catalog Number	Revision
1756-L55	11.71
1756-CNB/D	5.38.40

1756-CNBR/D	5.38.40
1756-ENBT	2.3
1757-SRM	3.29

11.70 Standard	
Release Notes attached below: 1756-RN582O	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Service Advisory 2004-08-003 in Answer ID 53320 • Service Advisory 2004-11-002 in Answer ID 53307 	
Catalog Number	Revision
1756-L55Mxx	11.70
1756-CNB/D	5.38.40
1756-CNBR/D	5.38.40
1756-ENBT	2.3
1757-SRM	3.29

11.60 Standard	
Release Notes attached below: 1756-RN582N	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Service Advisory 2004-08-003 in Answer ID 53320 • Service Advisory 2004-11-002 in Answer ID 53307 	
Catalog Number	Revision
1756-L55Mxx	11.60
1756-CNB/D	5.36
1756-CNBR/D	5.36
1757-SRM	3.25

11.52 Standard	
Release Notes attached below: 1756-RN582K	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Service Advisory 2004-08-003 in Answer ID 53320 • Service Advisory 2004-11-002 in Answer ID 53307 	

Catalog Number	Revision
1756-L55	11.52
1756-CNB/D	5.33
1756-CNBR/D	5.33
1757-SRM	3.13

8.90 Standard	
Release Notes attached below: 1756-RN612A	
Available for download from the Firmware Updates web site.	
Catalog Number	Revision
1756-L55	8.90
1756-CNB/D	5.32
1756-CNBR/D	5.32
1757-SRM	3.13

8.89 Standard	
Release Notes attached below: 1756-RN582I-EN-E	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Service Advisory 2004-08-003 in Answer ID 53320 • Service Advisory 2004-11-002 in Answer ID 53307 	
Catalog Number	Revision
1756-L55Mxx	8.89
1756-CNB/D	5.31
1756-CNBR/D	5.31
1757-SRM	3.13

8.88 Standard	
Release Notes attached below: 1756-RN581G	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Service Advisory 2004-08-003 in Answer ID 53320 • Service Advisory 2004-11-002 in Answer ID 53307 	
Catalog Number	Revision
1756-L55Mxx	8.88
1756-CN/D	5.30
1756-CNBR/D	5.30
1757-SRM	3.11

8.85 Standard	
Release Notes attached below: 1756-RN582F	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Service Advisory 2004-08-003 in Answer ID 53320 • Service Advisory 2004-11-002 in Answer ID 53307 	
Catalog Number	Revision
1756-L55	8.85
1756-CN/D	5.28
1756-CNBR/D	5.28
1757-SRM	2.15

8.84 Standard	
Release Notes attached below: 1756-RN582E	
Available upon special request, after reviewing: <ul style="list-style-type: none"> • Service Advisory 2004-08-003 in Answer ID 53320 • Service Advisory 2004-11-002 in Answer ID 53307 	
Catalog Number	Revision

1756-L55	8.84
1756-CNBR/D	5.28
1756-CNBR/D	5.28
1757-SRM	2.15

8.78 Standard

Available upon special request, after reviewing:

- Service Advisory 2004-08-003 in Answer ID [53320](#)
- Service Advisory 2004-11-002 in Answer ID [53307](#)

Catalog Number	Revision
1756-L55	8.78
1756-CNBR/D	5.28
1756-CNBR/D	5.28
1757-SRM	2.15

File Attachments

-  [1756-RN582E-EN-E.pdf](#) (216.75 KB)
-  [1756-RN582F-EN-E.pdf](#) (219.58 KB)
-  [1756-RN582G-EN-E.pdf](#) (233.2 KB)
-  [1756-RN582I-EN-E.pdf](#) (282.88 KB)
-  [1756-RN582N-EN-E.pdf](#) (286.97 KB)
-  [1756-RN582O-EN-E.pdf](#) (391.25 KB)
-  [1756-RN582P-EN-E.pdf](#) (348.96 KB)
-  [1756-RN582Q-EN-E.pdf](#) (352.8 KB)
-  [1756-RN608D-EN-E.pdf](#) (324.94 KB)
-  [1756-RN608E-EN-E.pdf](#) (271.91 KB)
-  [1756-RN608F-EN-E.pdf](#) (277.34 KB)
-  [1756-RN612A-EN-E.pdf](#) (361.68 KB)
-  [1756-RN628C-EN-E.pdf](#) (675.55 KB)
-  [1756-RN628D-EN-E.pdf](#) (549.58 KB)
-  [1756-RN628E-EN-E.pdf](#) (646 KB)
-  [1756-RN628F-EN-E.pdf](#) (558.47 KB)
-  [1756-RN628G-EN-E.pdf](#) (865.91 KB)
-  [1756-RN628J-EN-E.pdf](#) (668.79 KB)
-  [1756-RN628K-EN-E.pdf](#) (760.19 KB)
-  [1756-RN628M-EN-E.pdf](#) (573.25 KB)
-  [1756-RN650B-EN-E.pdf](#) (488.57 KB)
-  [1756-RN650C-EN-E.pdf](#) (881.65 KB)
-  [1756-RN650D-EN-E.pdf](#) (668.82 KB)
-  [1756-RN650E-EN-E.pdf](#) (683.09 KB)
-  [1756-RN668A-EN-E.pdf](#) (576.36 KB)

-  [1756-RN684A-EN-P.pdf](#) (2.22 MB)
-  [1756-RN684B-EN-P.pdf](#) (2.29 MB)
-  [1756-RN684C-EN-P.pdf](#) (1.58 MB)
-  [1756-RN684D-EN-P.pdf](#) (773.76 KB)
-  [1756-RN694A-EN-P.pdf](#) (941.88 KB)
-  [1756-RN694B-EN-P.pdf](#) (2.56 MB)
-  [1756-RN694C-EN-P.pdf](#) (845.95 KB)
-  [1756-RN608C-EN-E.pdf](#) (288.38 KB)
-  [1756-RN582K-EN-E.pdf](#) (295.23 KB)
-  [1756-RN694D-EN-P.pdf](#) (1.81 MB)

Product Tree for This Answer (expand/collapse)

DISCLAIMER

This knowledge base web site is intended to provide general technical information on a particular subject or subjects and is not an exhaustive treatment of such subjects. Accordingly, the information in this web site is not intended to constitute application, design, software or other professional engineering advice or services. Before making any decision or taking any action, which might affect your equipment, you should consult a qualified professional advisor.

ROCKWELL AUTOMATION DOES NOT WARRANT THE COMPLETENESS, TIMELINESS OR ACCURACY OF ANY OF THE DATA CONTAINED IN THIS WEB SITE AND MAY MAKE CHANGES THERETO AT ANY TIME IN ITS SOLE DISCRETION WITHOUT NOTICE. FURTHER, ALL INFORMATION CONVEYED HEREBY IS PROVIDED TO USERS "AS IS." IN NO EVENT SHALL ROCKWELL BE LIABLE FOR ANY DAMAGES OF ANY KIND INCLUDING DIRECT, INDIRECT, INCIDENTAL, CONSEQUENTIAL, LOSS PROFIT OR DAMAGE, EVEN IF ROCKWELL AUTOMATION HAVE BEEN ADVISED ON THE POSSIBILITY OF SUCH DAMAGES.

ROCKWELL AUTOMATION DISCLAIMS ALL WARRANTIES WHETHER EXPRESSED OR IMPLIED IN RESPECT OF THE INFORMATION (INCLUDING SOFTWARE) PROVIDED HEREBY, INCLUDING THE IMPLIED WARRANTIES OF FITNESS FOR A PARTICULAR PURPOSE, MERCHANTABILITY, AND NON-INFRINGEMENT. Note that certain jurisdictions do not countenance the exclusion of implied warranties; thus, this disclaimer may not apply to you.

This page is best viewed in Internet Explorer 7, Firefox 3.5, Chrome 4, Safari 4 or newer.